

Wire Tracker/CCTV Tester model CT 100-B

CT 100-B



- image display
- audio output
- wire tracing
- charge and charging indication
- low battery alarming
- automatically turn off
- flashlight function
- earphone output
- wire tracing sound level adjustable
- 2.0 inches TFT LCD
- automatic PAL/NTSC identifying
- 12V 500m emergency power output, with short circuit protection
- This device will turn off automatically within 8 minutes if there is no further operation of the key
- 1KM wire tracing distance: over 1 Km
- 3 built-in batteries of 3.7V 350mah
- 15V 1A power adaptor of 15V 1A



Transmitter audio signal is connected with the target wire while tracing with RJ11 interface, which generate a close loop audio signal field around the target wire loop, and the receiver will pick up the signal at the loop or the other end of the wire to find the target wire. This method features long distance and clear sound which helps the users to find the target wires effectively and quickly.

In testing the camera the device displays the images on the screen via its signal cable so that angle and range of the camera will be adjusted to the best position.

This device finds wide application in fields of camera mounting and wire tracing.

specification	transmitter	receiver
weight	132.2g	59.2g
size	64x31x119mm	48.6x26x177mm
battery	3.7V AAx3lithium battery	6F22 9V battery
Tracing signal transmit distance	>1km	
display mode	2.0-inch TFT LCD	
environment temperature in operation	-10 ~40°C (14 ~ 104°C)	
relative humidity	10-95%	
storage temperature	-20 ~ 60°C (-4~140°C)	